



## No hassle warranty

No waiting.

No shipping charges.

Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)

TRANSCAT

**•** Visit us at Transcat.com!

Data Sheet

35 Vantage Point Drive // Rochester, NY 14624 // Call 1.800.800.5001

# LM-100 Light Meter

The Amprobe LM-100 light meter measures the visible light from fluorescent, metal halide, high-pressure sodium or incandescent sources. It is a portable, easy-to-use digital light meter designed for simple one-hand operation reading in Lumen (lux) or footcandle (fc) units. The LM-100 measures a wide range of light up to 20,000 fc or lux with an accurate, high resolution of 0.01 fc/lux.

Use the LM-100 light meter to measure the illumination level in the interior and to switch off or reduce or increase the output level of lighting fixtures. Reduce the energy burden of the building by significantly increasing the efficiency of its lighting system.

One lux is the illumination from a one candela lamp perpendicular to a surface one meter squared at a distance of one meter. One fc is the illumination from a one candela lamp perpendicular to a surface one foot squared at a distance of one foot. 1 footcandle = 10.764 lux and 1 lux = 0.09290 footcandles

- Measure in Lux or Footcandles, front panel switchable
- Measuring Range to 20,0000 Lux or Foot candles
- Silicon photodiode sensor and filter
- **Data Hold to freeze reading on the digital display**
- MIN / MAX ability to show high and low readings
- Auto Power Off to save battery life
- Includes protective sensor cap
- Large, 3-1/2 digit display





### LM-100 Light Meter

## Data Sheet

#### **Specifications**

Accuracy at 23°C ± 5°C (73.4°F ± 5°F	<sup>-</sup> ), < 75% R.H.
Silicon photodiode and filter	
2.5 times per second	
20, 200, 2000, 20000, 200000 Lux	
20, 200, 2000, 20000 Foot candles	
± 3% (Calibrated to standard incandescent lamp at 2854°K)	
5	
	Characteristics
50	± 2%
	± 6%
	± 25%
5 1	5
Resolution	0.01 fc/lux
1 3 1	5
	ve polarity indication
(OL) or (-OL) is displayed	
Automatic	
The " $\overline{\Box}$ " is displayed when the ba	attery voltage drops below the operating level
Operating -10°C to 50°C (14°F to 1	
Storage -10°C to 50°C (14°F to 2	122°F), 0 to 70%RH
2000m, indoor operation	
9V NEDA 1604, IEC 6F22, JIS 006P b	attery
200 hours	
approx 6 min	
130 x 63 x 38 mm (5.1 x 2.5 x 1.5")	
80 x 55 x 29 mm (3.2 x 2.2 x 1.1")	
220 g (.48 lb.) include battery	
tions	
EN61326-1 This product complies w	ith requirements of the following European Community Directives
	patibility) and 73/23/EEC (Low Voltage) as amended by 93/68/EEC
	oise or intense electromagnetic fields in the vicinity of the equip-
	Silicon photodiode and filter 2.5 times per second 20, 200, 2000, 20000, 200000 Lux 20, 200, 2000, 20000 Foot candles ± 3% (Calibrated to standard incan 6% other visible light sources Angle deviation from cosine 30° 60° 80° Cosine Angular corrected per JIS C Resolution 3¾ digit liquid crystal display (LCD) 2.5 times per second for digital disp Automatic, positive implied, negati (OL) or (-OL) is displayed Automatic The "=="" is displayed when the ba Operating -10°C to 50°C (14°F to Storage -10°C to 50°C (14°F to 2000m, indoor operation 9V NEDA 1604, IEC 6F22, JIS 006P b 200 hours approx 6 min 130 x 63 x 38 mm (5.1 x 2.5 x 1.5") 80 x 55 x 29 mm (3.2 x 2.2 x 1.1") 220 g (.48 lb.) include battery tions EN61326-1 This product complies w 89/336/EEC (Electromagnetic Comp

EN61326-1 This product complies with requirements of the following European Community Directives: 89/336/EEC (Electromagnetic Compatibility) and 73/23/EEC (Low Voltage) as amended by 93/68/EEC (CE Marking). However, electrical noise or intense electromagnetic fields in the vicinity of the equipment may disturb the measurement circuit. Measuring instruments will also respond to unwanted signals that may be present within the measurement circuit. Users should exercise care and take appropriate precautions to avoid misleading results when making measurements in the presence of electronic interference.

> ©2008 Amprobe Test Tools. All rights reserved. 6/2008 3358154 Rev A

> > ► Visit us at Transcat.com!



**TRANSCAT**