

Supplement

Title:	365 Users	Supplement Issue:	6
Part Number:	3622684	Issue Date:	8/15
Print Date:	August 2010	Page Count:	5
Revision/Date:			

This supplement contains information necessary to ensure the accuracy of the above Users Manual.

Change #1, #2, 520

On page 3, under **Warning** add:

- **When the white wear indicator insulation shows through the clamp cable jacket, replace the clamp cable .**
- **When batteries are changed, ensure that the calibration seal in the battery compartment is not damaged. If damaged, the Meter may not be safe to use. Return the Meter to Fluke for replacement of the seal.**
- **Use Product-approved measurement category (CAT), voltage, and amperage rated accessories (probes, test leads, and adapters) for all measurements.**
- **Use the Clamp only on insulated conductors. Use caution around bare conductors or bus bars. To prevent electrical shock, do not touch the conductor.**

- **Do not exceed the Measurement Category (CAT) rating of the lowest rated individual component of a Product, probe, or accessory.**
- **Do not use a current measurement as an indication that a circuit is safe to touch. A voltage measurement is necessary to know if a circuit is hazardous.**
- **Do not use the Product above its rated frequency.**
- **Do not use in CAT III or CAT IV environments without the protective cap installed on test probe. The protective cap decreases the exposed probe metal to <4 mm. This decreases the possibility of arc flash from short circuits.**


Change #3

On page 4, add:

- **Measure a known voltage to verify product operation.**

Change #4, 64918, 486, 105

On page 5, add the following to the **Symbols** table:

	Conforms to relevant South Korean EMC Standards.
CAT II	Measurement Category II is applicable to test and measuring circuits connected directly to utilization points (socket outlets and similar points) of the low-voltage MAINS installation.
CAT IV	Measurement Category IV is applicable to test and measuring circuits connected at the source of the building's low-voltage MAINS installation.

On page 17, delete **Safety Compliance** and **Agency Approvals** and replace with:

Safety..... IEC 61010-1 Pollution Degree 2, IEC 61010-2-033
CAT III 600 V, IEC 61010-2-032

Electromagnetic Compatibility (EMC)

International..... IEC 61326-1: Portable Electromagnetic
Environment

CISPR 11: Group 1, Class A

Group 1: Equipment has intentionally generated and/or uses conductively-coupled radio frequency energy that is necessary for the internal function of the equipment itself.

Class A: Equipment is suitable for use in all establishments other than domestic and those directly connected to a low-voltage power supply network that supplies buildings used for domestic purposes. There may be potential difficulties in ensuring electromagnetic compatibility in other environments due to conducted and radiated disturbances.

Emissions that exceed the levels required by CISPR 11 can occur when the equipment is connected to a test object.

Korea (KCC)..... Class A Equipment (Industrial Broadcasting &
Communication Equipment)

Class A: Equipment meets requirements for industrial electromagnetic wave equipment and the seller or user should take notice of it. This equipment is intended for use in business environments and not to be used in homes.

USA (FCC) 47 CFR 15 subpart B. This product is considered an exempt device per clause 15.103.

Change #5,105

On page 6, replace CAT III with:

CAT III	Measurement Category III is applicable to test and measuring circuits connected to the distribution part of the building's low-voltage MAINS installation.
---------	--