

Manual Supplement

Manual Title:	77 Series IV Calibration	Supplement Issue:	2
Print Date:	September 2006	Issue Date:	4/13
Revision/Date:		Page Count:	2

This supplement contains information necessary to ensure the accuracy of the above manual. Enter the corrections in the manual if either one of the following conditions exist:

1. The revision letter stamped on the indicated PCA is equal to or higher than that given with each change.
2. No revision letter is indicated at the beginning of the change.

Change #1

On page 12, Table 2, under **Meter Response Beeper Off**, change step 8,

From:

0.47 V ac	0.53 V ac
-----------	-----------

To:

0.047 V ac	0.053 V ac
------------	------------

Change #2

On page 13, Table 2, make the following changes:

Under **5500 Output**, step 25 change:

From:

Apply 900 nF

To:

900 nF

Add a new step 26 and renumber the remaining steps accordingly:

26	➔ Diode Test ^[1]	2.0 V	1.978 V dc	2.022 V dc
----	-----------------------------	-------	------------	------------

Change #3, 63744, 65326

On page 3, replace the Symbols table with:

Symbols	Description	Symbols	Description
	AC (Alternating Current)		Fuse
	DC (Direct Current)		Conforms to European Union directives
	DC/AC		Conforms to relevant North American Safety Standards
	Earth ground		Double-insulated
	Risk of danger. Important information. See Manual		Hazardous Voltage
	Battery. (Low battery when shown on display)		Conforms to relevant Australian standards
	Inspected and licensed by TÜV Product Services		
	Conforms to relevant South Korean EMC Standards		
CAT II	Measurement Category II is applicable to test and measuring circuits connected directly to utilization points (socket outlets and similar points) of the low-voltage MAINS installation.		
CAT III	Measurement Category III is applicable to test and measuring circuits connected to the distribution part of the building's low-voltage MAINS installation.		
CAT IV	Measurement Category IV is applicable to test and measuring circuits connected at the source of the building's low-voltage MAINS installation.		

On page 4, remove **Surge Protection, Electromagnetic Compatibility, Safety Compliance and Certifications** and add:

- Safety** IEC 61010-1: 600 V CAT IV / 1000 V CAT III, Pollution Degree 2
- Electromagnetic Environment**..... IEC 61326-1: Portable
- Electromagnetic Compatibility** Applies to use in Korea only. Class A Equipment (Industrial Broadcasting & Communication Equipment) ^[1]

[1] This product meets requirements for industrial (Class A) electromagnetic wave equipment and the seller or user should take notice of it. This equipment is intended for use in business environments and is not to be used in homes.