## **R**alston Instruments

#### www.ralstoninst.com

# XTFT-CAPS

Cap and chain, S.S. (for any male Quick-test XT adapter)

Turn any Quick-test XT adapter into a permanent installation with the addition of a cap and chain

### Features

- Seals any male Quick-test XT adapter
- Install on any Quick-test XT adapter for permanent installation in the field
- Note that these are not compatible with QT or QS hoses. Please use only on Quick-test XT adapters
- Made in USA



**XTFT-CAPS** 

### **Specifications**

Pressure Range	0 to 10000 psi (0 to 689 bar)
End C1	Female Quick-test XT with Cap and Chain
Has Check Valve	No
Temperature range	0 to 225 °F (-18 to 107 °C)
Construction	Stainless Steel
Dimensions A	0.95 in (2.41 cm)
Dimensions B	0.75 in (1.91 cm)