

VF5 AC Voltage Detector

Megger®



- AC non-contact voltage detector
- 12V – 1000V voltage range
- Visual, audible and vibration warning of low and medium voltages
- Durable rubber over-moulded body
- IP67
- Screw-on battery cover
- Built-in bright-white LED torch
- CAT IV 1000V

DESCRIPTION

The Megger VF5 Voltage Detector is intended to be used to check for the presence of AC voltage, indicated by a bright red LED situated within the white nylon tip, an audible sounder, plus vibration alert.

The detector has both low voltage (12 – 1000 V) and medium voltage (100 – 1000 V) ranges.

The VF5 has the added advantage of a bright-white LED torch for use in poor light.

APPLICATION

Suitable for identifying live conductors, finding a break in a conductor or verifying a blown fuse while in circuit and detecting AC voltage at socket outlets, switches, circuit breakers, fuses, cables and luminaires.

SPECIFICATION

| | |
|--------------------------------------|---|
| Detection voltage range | 12 V AC to 1000 V AC, 100 V to 1000 V AC |
| Frequency range | 50/60 Hz |
| Batteries | 2 x AAA / LR03 1.5 V batteries |
| Ambient Operating temperature | 32 °F to 122 °F (0 °C to 50 °C) |
| Storage temperature | 14 °F to 140 °F (-10 °C to 60 °C) |
| Humidity | 80 % max |
| Altitude | 2000 metres |
| Pollution Degree | 2 |
| Safety Compliance | CAT IV 1000 V |
| Auto Power Off | 5 minutes |
| IP Rating | IP67 |

SALES OFFICE

Megger USA -
Valley Forge Corporate Center
2621 Van Buren Avenue, Norristown,
Pennsylvania, 19403, USA
T. 1-610 676 8500
F. 1-610-676-8610

VF5_DS_en_US_V01

www.megger.com
ISO 9001
The word 'Megger' is a registered
trademark

ORDERING INFORMATION

| Description | Part number |
|---|-----------------|
| VF5 Box of 12 | 1013-098 |
| (only available, as a box of 12, not as individual instruments) | |
| Included Accessories | |
| Batteries 2 x AAA | |